# VALUE SERIES<sup>®</sup>

## Electric Latch Retraction with Request to Exit Switch (ER EX)

The Electric Latch Retraction (ER EX) option is designed for entrance and exit doors with panic or fire exit hardware where remote unlocking, remote dogging, access control or automatic door operator is desired.



Wide Stile shown, for Narrow Stile, specify NS Option (for use on 36" and 48" doors with 2" stiles).

Available with V40 Rim and V50/V51 Surface Vertical Rod Exit Devices


Benefits		
<ul> <li>Durable design provides years of trouble free protection, saving on replacement costs</li> <li>Fast and easy installation saves time and money</li> </ul>	<ul> <li>Fits almost any door in any décor</li> <li>Patented mounting plate and strike locator replaces paper templates</li> </ul>	<ul> <li>Controls foot traffic, deters unauthorized exits, prevents loss and meets building code requirements</li> <li>Angled end cap deflects damage away from device</li> </ul>
Features		
Continuous Duty Motor - quiet operation	<ul> <li>Momentary or maintained latch and pushpad retraction</li> </ul>	<ul> <li>FC3 - Flexible 3' Conduit Kit, mounts to device end cap</li> </ul>
<ul> <li>Switches to monitor pushpad</li> </ul>	• Voltage - 24VDC	
Mechanical Options		
• 36 - Fits 36" Door Width (Std.)	<ul> <li>Available with 711 Base Rail</li> </ul>	<ul> <li>EH8 - Five-knuckle energy transfer hinge - 8 wires</li> </ul>
• 48 - Fits 48" Door Width	Extrusion	
• F - 3-Hour Fire Rated	<ul> <li>LF - Less Flex Conduit</li> </ul>	For full list of available mechanical options, see V40 Series How To Order page
• H - Hurricane Rated	<ul> <li>FC10 - Flexible 10' Conduit Kit, mounts to device end cap</li> </ul>	
• 99 - Surface Strike (Std.)		
• 98 - Semi Mortise Strike	• PT5 - Concealed mortise mount power transfer	
<ul> <li>Available with 628 Base Rail Extrusion (Std.)</li> </ul>		
<b>Electrical Options</b>		
• 81-800 - 1A Power Supply for single door 82-800 - 2A Power Supply for pair of simultaneous doors 83-800 - 2A Power Supply for two independent doors	<ul> <li>Latch Retraction power supplies are required and sold separately</li> </ul>	
Accessories		
SN1 - Sex Nut Fasteners	NSK - Narrow Stile Conversion Kit - Converts V40 to fit narrow stile	<b>N=T=Y</b>
• Outside Trim (see Value Series Trim Options)	glass door applications	A Century of Security 1923-2023

#### **Technical Information**

- · Door types Wood, Hollow Metal, Fiberglass or Aluminum
- Door thickness fits standard 1-3/4" - 2-1/4"
- Single door stile fits 3-1/2" minimum stile doors with 99 surface strike (std)
- · Machine and self-drilling screws (std)
- Voltage 24VDC

- Minimum wire gauge for 24VDC ER operation (these are minimum requirements - larger gauge wire is acceptable) Up to 50 feet: 20 gauge 51 -400 feet: 18 gauge 401 - 750 feet: 16 gauge 751 - 1000 feet: 14 gauge
- 0.18A to hold push pad and latch retracted
- 1A power supply 24VDC filtered and regulated power supply 1ER device 2ER devices if devices are staggered by 300mSec
- 2A power supply 24VDC filtered and regulated power supply 2ER devices 4ER devices if devices are staggered by 300mSec

#### **Dimensions**



### **Listings and Approvals**

See individual device (i.e. V40 Series) catalog page for fire and panic listings and windstorm ratings/ approvals

#### **Riser Diagram**

